

## 54ACTQ32QML Quiet Series Quad 2-Input OR Gate

Check for Samples: [54ACTQ32QML](#)

### FEATURES

- Radiation Features 54ACTQ32 Guaranteed to 100k rd(Si)
- $I_{CC}$  Reduced by 50%
- Minimum 4KV ESD Protection
- Guaranteed Simultaneous Switching Noise Level and Dynamic Threshold Performance
- Improved Latch-up Immunity
- Outputs Source/sink 24 mA
- ACTQ32 has TTL-compatible Inputs

### DESCRIPTION

The 'ACTQ32 contains four, 2-input OR gates and utilizes NSC Quiet Series technology to guarantee quiet output switching and improved dynamic threshold performance. FACT Quiet Series™ features GTO™ output control and undershoot corrector in addition to a split ground bus for superior ACMOS performance.

### Logic Symbol




Figure 1. IEEE/IEC

### Connection Diagram




Figure 2. Pin Assignment for DIP and Flatpak

Pin Names	Description
$A_n, B_n$	Inputs
$O_n$	Outputs



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

FACT is a trademark of Fairchild Semiconductor.

FACT Quiet Series is a trademark of Fairchild Semiconductor Corporation.

GTO is a trademark of dcl\_owner.

All other trademarks are the property of their respective owners.

**Table 1. Capacitance**

Symbol	Parameter	Max	Units	Conditions
C <sub>I</sub>	Input Capacitance	10.0	pF	V <sub>CC</sub> = Open
C <sub>PD</sub>	Power Dissipation Capacitance	72.0	pF	V <sub>CC</sub> = 5.0V



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

**Absolute Maximum Ratings**<sup>(1)</sup>

Supply Voltage (V <sub>CC</sub> )		-0.5V to +7.0V
DC Input Diode Current (I <sub>IK</sub> )	V <sub>I</sub> = -0.5V	-20 mA
	V <sub>I</sub> = V <sub>CC</sub> + 0.5V	+20 mA
DC Input Voltage (V <sub>I</sub> )		-0.5V to V <sub>CC</sub> + 0.5V
DC Output Diode Current (I <sub>OK</sub> )	V <sub>O</sub> = -0.5V	-20 mA
	V <sub>O</sub> = V <sub>CC</sub> + 0.5V	+20 mA
DC Output Voltage (V <sub>O</sub> )		-0.5V to V <sub>CC</sub> + 0.5V
DC Output Source or Sink Current (I <sub>O</sub> )		±50 mA
DC V <sub>CC</sub> or Ground Current per Output Pin (I <sub>CC</sub> or I <sub>Gnd</sub> )		±50 mA
Thermal Resistance, Junction to Case (θ <sub>JC</sub> )		See Mil-Std-1835
Storage Temperature (T <sub>Stg</sub> )		-65°C ≤ T <sub>A</sub> ≤ +150°C
Junction Temperature (T <sub>J</sub> )		175°C
Maximum Power Dissipation (P <sub>D</sub> )		500mW
Lead Temperature (soldering, 10 seconds)		300°C

- (1) Absolute maximum ratings are those values beyond which damage to the device may occur. The databook specifications should be met, without exception, to ensure that the system design is reliable over its power supply, temperature, and output/input loading variables. National does not recommend operation of FACT™ circuits outside databook specifications.

**Recommended Operating Conditions**

Supply Voltage (V <sub>CC</sub> )	4.5V to 5.5V
Input Voltage (V <sub>I</sub> )	0V to V <sub>CC</sub>
Output Voltage (V <sub>O</sub> )	0V to V <sub>CC</sub>
Operating Temperature (T <sub>A</sub> )	-55°C ≤ T <sub>A</sub> ≤ +125°C
Minimum Input Edge Rate (ΔV/Δt) V <sub>I</sub> from 0.8V to 2.0V V <sub>CC</sub> @ 4.5V, 5.5V	125 mV/ns
Maximum High Level Output Current (I <sub>OH</sub> )	-24mA
Maximum Low Level Output Current (I <sub>OL</sub> )	+24mA

**Radiation Features**

54ACTQ32JRQMLV	100 krad (Si)
54ACTQ32WRQMLV	100 krad (Si)

**Quality Conformance Inspection**

Mil-Std-883, Method 5005 - Group A

Subgroup	Description	Temp °C
1	Static tests at	25
2	Static tests at	125
3	Static tests at	-55

Subgroup	Description	Temp °C
4	Dynamic tests at	25
5	Dynamic tests at	125
6	Dynamic tests at	-55
7	Functional tests at	25
8A	Functional tests at	125
8B	Functional tests at	-55
9	Switching tests at	25
10	Switching tests at	125
11	Switching tests at	-55

### 54ACTQ32–QMLV RH Electrical Characteristics DC Parameters

The following conditions apply, unless otherwise specified.

DC:  $V_{CC} = 4.5V$  to  $5.5V$ , Temperature range  $-55^{\circ}C$  to  $125^{\circ}C$

Symbol	Parameter	Conditions	Notes	Min	Max	Units	Sub-groups
$I_{IH}$	High Level Input Current	$V_{CC} = 5.5V, V_{IH} = 5.5V$	See <sup>(1)(2)</sup>	0.1		$\mu A$	1
			See <sup>(1)(2)</sup>	1.0		$\mu A$	2, 3
$I_{IL}$	Low Level Input Current	$V_{CC} = 5.5V, V_{IL} = 0.0V$	See <sup>(1)(2)</sup>	-0.1		$\mu A$	1
			See <sup>(1)(2)</sup>	-1.0		$\mu A$	2, 3
$V_{OL}$	Low Level Output Voltage	$V_{CC} = 4.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = 50.0\mu A$	See <sup>(1)(2)</sup>	0.1		V	1, 2, 3
			See <sup>(1)(2)</sup>	0.1		V	1, 2, 3
		$V_{CC} = 4.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = 24.0mA$	See <sup>(1)(2)</sup>	0.36		V	1
			See <sup>(1)(2)</sup>	0.5		V	2, 3
		$V_{CC} = 5.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = 24.0mA$	See <sup>(1)(2)</sup>	0.36		V	1
			See <sup>(1)(2)</sup>	0.5		V	2, 3
$V_{IOL}$	Dynamic Output Current LOW	$V_{CC} = 5.5V, V_{IH} = 5.5V, V_{IL} = 0.0V, I_{OL} = 50.0mA$	See <sup>(1)(2)(3)</sup>		1.65	V	1, 2, 3
$V_{OH}$	High Level Output Voltage	$V_{CC} = 4.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = -50.0\mu A$	See <sup>(1)(2)</sup>	4.40		V	1, 2, 3
			See <sup>(1)(2)</sup>	5.40		V	1, 2, 3
		$V_{CC} = 4.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = -24.0mA$	See <sup>(1)(2)</sup>	3.86		V	1
			See <sup>(1)(2)</sup>	3.70		V	2, 3
		$V_{CC} = 5.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = -24.0mA$	See <sup>(1)(2)</sup>	4.86		V	1
			See <sup>(1)(2)</sup>	4.70		V	2, 3
$V_{IOH}$	Dynamic Output Current HIGH	$V_{CC} = 5.5V, V_{IH} = 2.0V, V_{IL} = 0.8V, I_{OL} = -50.0mA$	See <sup>(1)(2)(3)</sup>	3.85		V	1, 2, 3
$I_{CCH}$	Supply Current	$V_{CC} = 5.5V, V_{IH} = 5.5V$	See <sup>(1)(2)</sup>	100		nA	1
			See <sup>(1)(2)</sup>	40		$\mu A$	2, 3
$I_{CCL}$	Supply Current	$V_{CC} = 5.5V, V_{IH} = 0.0V$	See <sup>(1)(2)</sup>	100		nA	1
			See <sup>(1)(2)</sup>	40		$\mu A$	2, 3
$I_{CCF}$	Supply Current Functional	$V_{CC} = 5.5V, V_{IH} = 0.0V$	See <sup>(1)(2)</sup>	100		nA	1
			See <sup>(1)(2)</sup>	40		$\mu A$	2, 3
$I_{CCT}$	Supply Current	$V_{CC} = 5.5V, V_{IH} = 3.4V$	See <sup>(1)(2)</sup>	1.0		mA	1
			See <sup>(1)(2)</sup>	1.6		mA	2, 3
$V_{IKL}$		$V_{CC} = 4.5V, I_{KL} = -18mA$	See <sup>(1)(2)</sup>	-1.2		V	1, 2, 3

(1) Screen tested 100% on each device @  $+25^{\circ}C$  &  $+125^{\circ}C$  temperature, Subgroup 1, 2, 7 & 8.

(2) Sample tested (TM5005, Table 1) on each manufacturing lot @  $+25^{\circ}C, +125^{\circ}C, -55^{\circ}C$ , Subgroups A1, 2, 3, 7, & 8

(3) Transmission line driving test, guardbanded limits set for  $+25^{\circ}C$ , 2mS duration maximum

### 54ACTQ32–QMLV RH Electrical Characteristics DC Parameters (continued)

The following conditions apply, unless otherwise specified.

DC:  $V_{CC} = 4.5V$  to  $5.5V$ , Temperature range  $-55^{\circ}C$  to  $125^{\circ}C$

Symbol	Parameter	Conditions	Notes	Min	Max	Units	Sub-groups
$V_{IKH}$		$V_{CC} = 4.5V$ , $I_{KH} = 18mA$	See <sup>(1)(2)</sup>		5.7	V	1, 2, 3
$V_{ILD}$	Maximum Low Level Dynamic Input Voltage	$V_{CC} = 5.0V$ , Load $50pF / 500\Omega$	See <sup>(4)(5)</sup>		0.8	V	4
$V_{IHD}$	Minimum High Level Dynamic Input Voltage	$V_{CC} = 5.0V$ , Load $50pF / 500\Omega$	See <sup>(4)(5)</sup>	2.2		V	4
$V_{OLP}$	Quiet Output Maximum Dynamic $V_{OL}$	$V_{CC} = 5.0V$ , Load $50pF / 500\Omega$	See <sup>(4)(6)</sup>		1.5	V	4
$V_{OLV}$	Quiet Output Minimum Dynamic $V_{OL}$	$V_{CC} = 5.0V$ , Load $50pF / 500\Omega$	See <sup>(4)(6)</sup>		-1.2	V	4

(4) Guaranteed but not tested. Design characterization data

(5) Maximum number of data inputs (n) switching. (n-1) inputs switching 0V to 3V. Input-Under-Test switching 3V to threshold ( $V_{ILD}$ , 0V to threshold  $V_{IHD}$ ,  $f = 1MHz$ )

(6) Maximum number of outputs defined as (n) switching. Data inputs are driven 0V to 3V. One output @  $V_{OL}$

### 54ACTQ32–QMLV RH Electrical Characteristics AC Parameters

The following conditions apply, unless otherwise specified.

AC:  $C_L = 50pF$ ,  $R_L = 500\Omega$ ,  $t_{Rise} = 3.0nS$ ,  $t_{Fall} = 3.0nS$

Symbol	Parameter	Conditions	Notes	Min	Max	Units	Sub-groups
$t_{PLH}$	Propagation Delay	$V_{CC} = 4.5V$	See <sup>(1)(2)(3)</sup>	1.5	7.0	ns	9
			See <sup>(1)(2)(3)</sup>	1.5	7.5	ns	10, 11
$t_{PHL}$	Propagation Delay	$V_{CC} = 4.5V$	See <sup>(1)(2)(3)</sup>	1.5	7.0	ns	9
			See <sup>(1)(2)(3)</sup>	1.5	7.5	ns	10, 11
$t_{OSLH}$	Output to Output Skew	$V_{CC} = 4.5V$	See <sup>(4)</sup>		1.0	ns	9, 10, 11
$t_{OSHL}$	Output to Output Skew	$V_{CC} = 4.5V$	See <sup>(4)</sup>		1.0	ns	9, 10, 11

(1) Screen tested 100% on each device @  $+25^{\circ}C$ , only. Subgroup A9.

(2) Sample tested (TM5005, Table 1) on each manufacturing lot @  $+25^{\circ}C$ ,  $+125^{\circ}C$ , &  $-55^{\circ}C$  temperature, Subgroups A9, 10 & 11

(3)  $+25^{\circ}C$ , &  $+125^{\circ}C$  minimum limits guaranteed for 5.5V by guardbanding 4.5V minimum limits.

(4) Guaranteed but not tested. Design characterization data

### 54ACTQ32–QMLV RH Electrical Characteristics Delta Parameters

The following conditions apply, unless otherwise specified.

Burn-in and operating life test, Delta parameters ( $+25^{\circ}C$ )

Symbol	Parameter	Conditions	Notes	Min	Max	Units	Sub-groups
$I_{CCH}$	Quiescent supply current		See <sup>(1)(2)</sup>		$\pm 100$	nA	1
$I_{CCL}$	Quiescent supply current		See <sup>(1)(2)</sup>		$\pm 100$	nA	1

(1) These parameters shall be recorded before and after the required burn-in and life tests to determine the delta limits.

(2) This limit may not be production tested.

**REVISION HISTORY SECTION**

Date Released	Revision	Section	Originator	Changes
12/14/05	A	New Release, Corporate format. Additions made in conversion: Radiation Features, Delta parameter table in electricals and Notes 11 & 12.	L. Lytle	1 MDS datasheet converted into one Corp. datasheet format. Additions made in conversion: Radiation Features, pg 3, Delta parameter table in electricals and Notes 11 & 12 , pg 6 to reflect SMD. MV54ACTQ32–X Rev 1A0 will be archived.
04/08/13	A	All		Changed layout of National Data Sheet to TI format.

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DLP® Products	<a href="http://www.dlp.com">www.dlp.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
OMAP Applications Processors	<a href="http://www.ti.com/omap">www.ti.com/omap</a>
Wireless Connectivity	<a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a>

### Applications

Automotive and Transportation	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Communications and Telecom	<a href="http://www.ti.com/communications">www.ti.com/communications</a>
Computers and Peripherals	<a href="http://www.ti.com/computers">www.ti.com/computers</a>
Consumer Electronics	<a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>
Energy and Lighting	<a href="http://www.ti.com/energy">www.ti.com/energy</a>
Industrial	<a href="http://www.ti.com/industrial">www.ti.com/industrial</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Space, Avionics and Defense	<a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a>
Video and Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)