

LF13006,LF13007

LF13006 LF13007 Digital Gain Set



Literature Number: SNOSBD2A

LF13006/LF13007 Digital Gain Set

General Description

The LF13006 and LF13007 are precision digital gain sets used for accurately setting non-inverting op amp gains. Gains are set with a 3-bit digital word which can be latched in with $\overline{WR}$ and $\overline{CS}$ pins. All digital inputs are TTL and CMOS compatible.

The LF13006 shown below will set binary scaled gains of 1, 2, 4, 8, 16, 32, 64, and 128. The LF13007 will set gains of 1, 2, 5, 10, 20, 50, and 100 (a common attenuator sequence). In addition, both versions have several taps and two uncommitted matching resistors that allow customization of the gain.


The gains are set with precision thin film resistors. The low temperature coefficient of the thin film resistors and their excellent tracking result in gain ratios which are virtually independent of temperature.

The LF13006, LF13007 used in conjunction with an amplifier not only satisfies the need for a digitally programmable amplifier in microprocessor based systems, but is also useful for discrete applications, eliminating the need to find 0.5% resistors in the ratio of 100 to 1 which track each other over temperature.

Features

- TTL and CMOS compatible logic levels
- Microprocessor compatible
- Gain error 0.5% max
- Binary or scope knob gains
- Wide supply range + 5V to $\pm 18V$
- Packaged in 16-pin DIP

Block Diagram and Typical Application (LF13006)



Note: $R \approx 15 \text{ k}\Omega$

Order Number LF13006N or LF13007N
See NS Package Number N16A

TL/H/5114-1

Absolute Maximum Ratings

If Military/Aerospace specified devices are required, please contact the National Semiconductor Sales Office/Distributors for availability and specifications.

Supply Voltage, V^+ to V^-	36V
Supply Voltage, V^+ to GND	25V
Voltage at Any Digital Input	V^+ to GND
Analog Voltage	V^+ to ($V^- + 2V$)

Operating Ratings (Note 1)

Operating Temperature Range	-40°C to $+85^\circ\text{C}$
Lead Temp. (Soldering, 10 seconds)	260°C

Electrical Characteristics (Note 2)

Parameter	Conditions	Typ (Note 3)	Tested Limit (Note 4)	Design Limit (Note 5)	Units
Gain Error	$A_{OUT} = \pm 10V$ ANA GND = 0V $I_{INPUT} < 10 \text{ nA}$	0.3	0.5	0.5	%(max)
Gain Temperature Coefficient	$A_{OUT} = \pm 10V$ ANA GND = 0V	0.001			%/ $^\circ\text{C}$
Digital Input Voltage Low High		1.4 1.6	0.8 2.0	0.8 2.0	V(max) V(min)
Digital Input Current Low High	$V_{IL} = 0V$ $V_{IH} = 5V$	-38 0.0001	-100 1	-100 1	$\mu\text{A}(\text{max})$ $\mu\text{A}(\text{max})$
Positive Power Supply Current	All Logic Inputs Low	2	5	5	mA(max)
Negative Power Supply Current	All Logic Inputs Low	-1.7	-5	-5	mA(max)
Write Pulse Width, t_W	$V_{IL} = 0V$, $V_{IH} = 5V$		150		ns(min)
Chip Select Set-Up Time, t_{CS}	$V_{IL} = 0V$, $V_{IH} = 5V$		250		ns(min)
Chip Select Hold Time, t_{CH}	$V_{IL} = 0V$, $V_{IH} = 5V$		0		ns(min)
DIG IN Set-Up Time, t_{DS}	$V_{IL} = 0V$, $V_{IH} = 5V$		150		ns(min)
DIG IN Hold Time, t_{DH}	$V_{IL} = 0V$, $V_{IH} = 5V$		60		ns(min)
Switching Time for Gain Change	(Note 4)	200			ns(max)
Switch On Resistance		3			$k\Omega$
Unit Resistance, R		15	12-18		$k\Omega$
R1 and R2 Mismatch		0.3	0.5	0.5	%(max)
R1/R2 Temperature Coefficient		0.001			%/ $^\circ\text{C}$

Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. DC and AC electrical specifications do not apply when operating the device beyond its specified operating conditions.

Note 2: Parameters are specified at $V^+ = 15V$ and $V^- = -15V$. Min V^+ to ground voltage is 5V. Min V^+ to V^- voltage is 5V. **Boldface numbers apply over full operating temperature ranges.** All other numbers apply at $T_A = T_J = 25^\circ\text{C}$.

Note 3: Typicals are at 25°C and represent most likely parametric norm.

Note 4: Guaranteed and 100% production tested.

Note 5: Guaranteed (but not 100% production tested) over the operating temperature. These limits are not used to calculate outgoing quality levels.


Note 6: Settling time for gain change is the switching time for gain change plus settling time (see section on Settling Time).

Note 7: WR minimum high threshold voltage increases to 2.4V under the extreme conditions when all three digital inputs are simultaneously taken from 0V to 5V at a slew rate of greater than $500V/\mu\text{S}$.


GAIN TABLE

Digital Input			Gain			
			LF13006		LF13007	
DIG in 3	DIG in 2	DIG in 1	A_{OUT}	B_{OUT}	A_{OUT}	B_{OUT}
0	0	0	1	1	1	1
0	0	1	2	1.25	1.25	1
0	1	0	4	2.5	2	1.6
0	1	1	8	5	5	4
1	0	0	16	10	10	8
1	0	1	32	20	20	16
1	1	0	64	40	50	40
1	1	1	128	80	100	80

Connection Diagram




Switching Waveforms



TL/H/5114-3

Block Diagram and Typical Application (Continued) (LF13007)




TL/H/5114-4


Note: $R \approx 15 \text{ k}\Omega$

Typical Performance Characteristics


Positive Power Supply Current vs Temperature




Negative Power Supply Current vs Temperature




Digital Input Threshold vs Temperature




Logical 0 Input Bias Current vs Temperature




Digital Input Threshold vs Supply Voltage




Write Width, t_w



Data Set-Up Time, t_{DS}



Chip Select Set-Up Time, t_{CS}



TL/H/5114-5

Application Information

FLOW-THROUGH OPERATION

THE LF13006, LF13007 can be operated with control lines CS and WR grounded. In this mode new data on the digital inputs will immediately set the new gain value. Input data cannot be latched in this mode.

INPUT CURRENT


Current flowing through the input (pin 2) due to bias current of the op amp will result in a gain error due to switch impedance. Normally this error is very small. For example, 10 nA of bias current flowing through 3 kΩ of switch resistance will result in an error of 30 μV at the summing node. However, applications that have significant current flowing through the input must take this effect into account.

SETTLING TIME

Settling time is a function of the particular op amp used with the LF13006/7 and the gain that is selected. It can be optimized and stability problems can be prevented through the




use of a lead capacitor from the inverting input to the output of the amplifier. A lead capacitor is effective whenever the feedback around an amplifier is resistive, whether with discrete resistors or with the LF13006/7. It compensates for the feedback pole created by the parallel resistance and capacitance from the inverting input of the op amp to AC ground.

Settling Time Test Circuit



TL/H/5114-6

Typical Settling Time Curves




TL/H/5114-7

* Unstable at C_L less than 2 pF

Typical Applications

Variable Capacitance Multiplier


$C_{\text{effective}} = C1(\text{gain set } \#)$
Note: Output swing at input op amp is multiplied by set gain. Signal range may be limited.



TL/H/5114-8

Variable Time Constant Filter


Time constant = $\frac{R}{N} C1$
 $N = \text{setting of LF13006}$
(range = $\frac{1}{128}$ to 1)



TL/H/5114-9

Typical Applications (Continued)


Programmable Current Source



TL/H/5114-10

$$I_{OUT} = \frac{1.2V}{120\Omega} \left[\frac{1}{\text{gain set \#}} \right]$$


Inverting Gains



TL/H/5114-12

Inverting gain with high input impedance can be obtained with the LF13006, LF13007 by using the two on-board resistors and a dual op amp as shown.


Switchable Gain of ± 1



TL/H/5114-11

Note: Digital code = 000, $V_{OUT} = V_{IN}$;
Digital code = 001, $V_{OUT} = -V_{IN}$

Programmable Differential Amp




TL/H/5114-13

Note 1: Actual gain = set gain - 1
since LF13006s are in
"inverting mode".


Note 2: Set gain must be
same on both LF13006s.

Typical Applications (Continued)


Altered Gain Range



One Octave per Bit Function Generator



Variable Gains of Almost 1




GAINS

A _{OUT}	B _{OUT}
1	1
1.8	1.2
3	2
4.5	3
6	4
7.2	4.8
8	5.33
8.47	5.65


GAINS

9
1.8
1.29
1.125
1.059
1.029
1.014
1.007

Programmable Instrumentation Amp




Attenuator (0 dB to -42 dB in 6 dB steps)



Note 1: $V_{OUT} = N(A - B)$, N = set gain.
Note 2: All 10k resistors 0.1% matched.

Physical Dimensions inches (millimeters)



Molded Dual-In-Line Package (N)
Order Number LF13006N or LF13007N
NS Package Number N16A

N16A (REV E)

LIFE SUPPORT POLICY

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.



National Semiconductor Corporation
 1111 West Bardin Road
 Arlington, TX 76017
 Tel: (800) 272-9959
 Fax: 1(800) 737-7018

National Semiconductor Europe
 Fax: (+49) 0-180-530 85 86
 Email: cnjwge@tevm2.nsc.com
 Deutsch Tel: (+49) 0-180-530 85 85
 English Tel: (+49) 0-180-532 78 32
 Français Tel: (+49) 0-180-532 93 58
 Italiano Tel: (+49) 0-180-534 16 80

National Semiconductor Hong Kong Ltd.
 19th Floor, Straight Block,
 Ocean Centre, 5 Canton Rd.
 Tsimshatsui, Kowloon
 Hong Kong
 Tel: (852) 2737-1600
 Fax: (852) 2736-9960

National Semiconductor Japan Ltd.
 Tel: 81-043-299-2309
 Fax: 81-043-299-2408

National does not assume any responsibility for use of any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Transportation and Automotive	www.ti.com/automotive
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2011, Texas Instruments Incorporated